


DHB1BRC



DVB1BR


Scan For  
Video


### IN BOX® FOR NEW BRICK INCLUDES

Box with weatherproof in use extra duty cover, adapter sleeve, installed bug plugs, (1) standard duplex and (1) standard GFCI face plate, installation screws, (1) NM cable connector, and (1) roll of caulk, disposable mud cover.

## Low Profile In Box® with Adapter Sleeve for New Brick

22.0 cubic inch recessed electrical box with extra duty weatherproof in use cover for new brick construction. Includes a protective adapter sleeve that keeps mortar out. Non-metallic cover and base. Accepts most single-gang wiring devices and uses standard indoor wall plates or a GFCI cover plate. White box and cover are textured/paintable. UV rated plastic for long outdoor life. Compatible with DBHC and DBHW extra duty replacement covers on K-17.

CATALOG NUMBER	UPC/DCI/NAED MFG #018997	DESCRIPTION/ COLORS	UNIT	STD PKG	DIM A	DIM B	DIM C	DIM D	DIM E
DHB1C	54880	Horiz./Clear Cover/White Box	1	4	4.934	7.186	5.283	1.658	3.625
DHB1W	54882	Horiz./White Cover/White Box	1	4	4.934	7.186	5.283	1.658	3.625
DHB1BRC	54881	Horiz./Clear Cover/Brown Box	1	4	4.934	7.186	5.283	1.658	3.625
DHB1BR	54875	Horiz./Brown Cover/Brown Box	1	4	4.934	7.186	5.283	1.658	3.625
DVB1C	43609	Vertical/Clear Cover/White Box	1	4	7.186	4.934	5.283	1.658	3.625
DVB1W	43620	Vertical/White Cover/White Box	1	4	7.186	4.934	5.283	1.658	3.625
DVB1BRC	43608	Vertical/Clear Cover/Brown Box	1	4	7.186	4.934	5.283	1.658	3.625
DVB1BR	43595	Vertical/Brown Cover/Brown Box	1	4	7.186	4.934	5.283	1.658	3.625



E170558 LR49636

PATENTED.

MADE IN USA.

ADDITIONAL PATENTS  
PENDING.

**Note: Meets NEC section 406.9 (B) for the protection of exterior outlets where an extra duty weatherproof in use cover is required for 15 or 20 AMP receptacles installed outdoors.** Add suffix "GC" to Catalog # when ordering in Canada, for example DHB1CGC.

### FEATURES AND BENEFITS

- Adapter sleeve, with loops in back for tying off cable, keeps mortar out of the box while brick mason works
- In Box®'s one piece assembly replaces the installation of an electrical box and bubble cover assembly
- The clean In Box® slips into the sleeve for easy installation
- No gaskets required
- Built in anchor tabs seat IN BOX sleeve into mortar for a super secure installation
- Installs in the wall, so less of it shows outside
- Install option: Cover is removable for easier device installation
- Weatherproof in use
- Extra duty



Bug Plugs ship installed in all In BOX® styles to seal unused cord hole openings.

### INSTALLATION INSTRUCTIONS



Mortar in adapter sleeve. Pull wire and tie off to loop in adapter sleeve.



When ready to complete, apply supplied caulk as shown and press around edges of adapter sleeve.



Install the supplied NM cable connector and wire. Insert the clean In Box® into the sleeve.



Attach In Box® with screws provided. Install wiring device per manufacturer's instructions, Local and National Electrical Codes.



Accepts most single gang wiring devices, and uses a standard indoor wall plate. DHB1C shown.



Weatherproof in use. DHB1BRC shown. In Box® Saves Time. Looks Great!

